

UNIX-FW50

HEDBOX UNIX-FW50 V-LOCK MOUNT PROFESSIONAL CINE BATTERY PLATE WITH 3X D-TAP (14.8V/10A) + 1 X USB (5.1V/2.1A) AND 1X BREAKAWAY 50CM DC7.2V CABLE WITH FW50 DUMMY HOUSING

OVERVIEW:

Hedbox **UNIX-FW50** V-Lock Mount Professional Cine Battery Plate with 1 x USB (5.1V/2.1A) + 3x D-Tap (14.8V/10A) and **1x Breakaway 50cm DC7.2V Cable with FW50 dummy housing.**

UNIX Professional Cine Battery V-Mount Plate enables the use of V-Lock battery packs on cameras and/or numerous professional peripherals simultaneously. Featuring a high-quality aluminium v-lock release, Hedbox UNIX plates are designed and tested for up to 10,000 battery cycles.

Three (3) D-Tap DC Power Outputs provide 14.8V / 10A for extra devices and peripherals such as on-board recorders, LED lights, monitors, remote follow focus, wireless transmitters etc. A built-in USB 5V / 2.1A Power Output is located on the top of the UNIX plate.

Designed with versatility in mind UNIX plates have multiple mounting holes to provide universal camera connection or peripheral mounting – 4x M3x12 screws are included with UNIX to mount the plate as required. The **UNIX-FW50** includes a hard-wired 50cm DC7.2V Cable with FW50 dummy housing, that can be used to power Sony Alpha Cameras and other professional photo/video devices that use Sony FW50 battery connections...

FEATURES:

Supplied Breakaway 50cm DC7.2V Cable with FW50 dummy housing

With an installed breakaway DC 7.2V / 3.5A / 25W power cable, UNIX-FW50 can be used to power Sony Alpha Cameras and devices in the video and photo market. The breakaway cable is a 50cm long, with FW50 dummy housing.

High Quality Aluminium V-lock release

Adopting technology that allowed us to use a high-quality aluminum alloy V-lock release, the lock and unlock provides up to 10,000 cycles for a V-mount battery on the Unix plate.

3 x D-Tap DC Power Output

Unix provides three D-Tap 14.8V / 10A DC power outputs. Three D-taps allow for extra powering for cameras, on board recorders, LED lights, monitors, remote follow focus, wireless transition systems, etc.

Multiple Mounting holes for universal camera connection

With multiple mounting holes, (4 x M3x12 screws provided) Unix is able to mount on to any device or camera connection.

Build-in USB 5V / 2.1A Power Out Socket

The USB 5V / 2.1A output can be used to power any external USB electronic devices. This function allows you to use the Unix V-lock plate like a power station to charge your cell phone, tablet, or any other electronic devices that can be powered with USB 5V / 2.1A power.

INCLUDED IN BOX:

- 1 X **UNIX-FW50** V-MOUNT PLATE WITH DC7.2V BREAKAWAY 50CM CABLE WITH FW50 DUMMY HOUSING
- 1 X SET SCREW M3X12 (4PCS)
- 1 X USER MANUAL
- 1 X 2 YEAR LIMITED MANUFACTURER'S WARRANTY

SPECIFICATION:

Model :	UNIX-FW50 V-Mount Adapter Power Plate
Battery Mount :	V-Lock Mount
D-Tap Power Out 1 :	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
D-Tap Power Out 2 :	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
D-Tap Power Out 3 :	DC 12V ~ 16.8V / 10A / 148W (Max) unregulated
USB Output :	DC 5V / 2.1A /10W (Max)
Breakaway DC Cable :	DC 7.2V / 3.5A / 25W (Max) 50cm (length) with FW50 dummy housing
V-lock release :	High Quality Aluminium Alloy
Operating Temperature :	-20°C to +45°C (-4°F to +113°F)
Dimensions (WxDxH) :	146 x 102 x 26 mm
Weight :	~ 185 g
Mounting :	Multiple mounting holes for universal camera connection